

## Содержание

Добавление программы в автозагрузку .....	3
---	---



## Добавление программы в автозагрузку

Для добавления программы в автозагрузку, необходимо добавить в каталог buildroot/board/rockchip/px30/fs-overlay-64/etc/init.d при сборке, при прошивке burn/add\_for\_burn\_sd/upper/etc/init.d, либо на готовой флешке в каталог /etc/init.d/, в разделе на 1ГБ, скрипт запуска вашего приложения, примерный код запуска с weston приведен ниже.

Пользовательский скрипт нужно назвать в формате «S99...». Если у вас уже запущен weston, то его не надо запускать второй раз.

```
#!/bin/sh
#
# Application description ...
#
# Load default env variables from profiles(e.g.
# /etc/profile.d/weston.sh)
. /etc/profile

case "$1" in
    start)

        export XDG_RUNTIME_DIR=${XDG_RUNTIME_DIR:-/var/run}
        export QT_QPA_PLATFORM=${QT_QPA_PLATFORM:-wayland}

        weston --tty=2 --idle-time=0&
        {
            # Wait for weston ready
            while [ ! -e ${XDG_RUNTIME_DIR}/wayland-0 ]; do
                sleep .1
            done
            **ЗАПУСК ВАШЕГО ПРИЛОЖЕНИЯ**
        }&
        ;;
    stop)
        **ОСТАНОВКА ВАШЕГО ПРИЛОЖЕНИЯ
        ;;
    *)
        echo "Usage: $0 {start|stop}"
        exit 1
        ;;
esac
exit 0
```

Пример скрипта:

```
#!/bin/sh
#
```

```
#  
  
. /etc/profile  
  
case "$1" in  
    start)  
  
        export XDG_RUNTIME_DIR=${XDG_RUNTIME_DIR:-/var/run}  
        export QT_QPA_PLATFORM=${QT_QPA_PLATFORM:-wayland}  
  
        # Wait for weston ready  
        while [ ! -e ${XDG_RUNTIME_DIR}/wayland-0 ]; do  
            sleep .1  
        done  
        /mnt/store/a7server/app&  
        ;;  
    stop)  
        killall app  
        ;;  
    *)  
        echo "Usage: $0 {start|stop}"  
        exit 1  
        ;;  
esac  
exit 0
```