



Co	ле	ржа	ние
-		P/110	

http://wiki.inmys.ru/ 1 Printed on 2025/12/15 04:23







Добавление программы в автозагрузку

Для добавления программы в автозагрузку, необходимо добавить в каталог buildroot/board/rockchip/px30/fs-overlay-64/etc/init.d при сборке, при прошивке burn/add_for_burn_sd/upper/etc/init.d, либо на готовой флешке в каталог /etc/init.d/, в разделе на 1Γ Б, скрипт запуска вашего приложения, примерный код запуска с weston приведен ниже.

Пользовательский скрипт нужно назвать в формате «S99...». Если у вас уже запущен weston, то его не надо запускать второй раз.

```
#!/bin/sh
# Application description ...
# Load default env variables from profiles(e.g.
/etc/profile.d/weston.sh)
. /etc/profile
case "$1" in
  start)
        export XDG RUNTIME DIR=${XDG RUNTIME DIR:-/var/run}
        export QT QPA PLATFORM=${QT QPA PLATFORM:-wayland}
        weston --tty=2 --idle-time=0&
        {
            # Wait for weston ready
            while [ ! -e ${XDG RUNTIME DIR}/wayland-0 ]; do
                sleep .1
            done
      **ЗАПУСК ВАШЕГО ПРИЛОЖЕНИЯ**
        }&
    ;;
  stop)
    ** ОСТАНОВКА ВАШЕГО ПРИЛОЖЕНИЯ
        ;;
  *)
        echo "Usage: $0 {start|stop}"
        exit 1
        ;;
esac
exit 0
```

Пример скрипта:

```
#!/bin/sh
#
```

http://wiki.inmys.ru/ 3 Printed on 2025/12/15 04:23





```
#
. /etc/profile
case "$1" in
  start)
        export XDG_RUNTIME_DIR=${XDG_RUNTIME_DIR:-/var/run}
        export QT_QPA_PLATFORM=${QT_QPA_PLATFORM:-wayland}
        # Wait for weston ready
        while [ ! -e ${XDG_RUNTIME_DIR}/wayland-0 ]; do
            sleep .1
        done
        /mnt/store/a7server/app&
    ;;
  stop)
        killall app
        ;;
  *)
        echo "Usage: $0 {start|stop}"
        exit 1
        ;;
esac
exit 0
```