

Содержание

Добавление программы в автозагрузку	3
---	---

Добавление программы в автозагрузку

Для добавления программы в автозагрузку, необходимо добавить в каталог `buildroot/board/rockchip/px30/fs-overlay-64/etc/init.d` при сборке, при прошивке `burn/add_for_burn_sd/upper/etc/init.d`, либо на готовой флешке в каталог `/etc/init.d/`, в разделе на 1ГБ, скрипт запуска вашего приложения, примерный код запуска с `weston` приведен ниже.

Пользовательский скрипт нужно назвать в формате «S99...». Если у вас уже запущен `weston`, то его не надо запускать второй раз.

```
#!/bin/sh
#
# Application description ...
#

# Load default env variables from profiles(e.g.
/etc/profile.d/weston.sh)
. /etc/profile

case "$1" in
  start)

    export XDG_RUNTIME_DIR=${XDG_RUNTIME_DIR:-/var/run}
    export QT_QPA_PLATFORM=${QT_QPA_PLATFORM:-wayland}

    weston --tty=2 --idle-time=0&
    {
      # Wait for weston ready
      while [ ! -e ${XDG_RUNTIME_DIR}/wayland-0 ]; do
        sleep .1
      done
      **ЗАПУСК ВАШЕГО ПРИЛОЖЕНИЯ**
    }&
    ;;
  stop)
    **ОСТАНОВКА ВАШЕГО ПРИЛОЖЕНИЯ**
    ;;
  *)
    echo "Usage: $0 {start|stop}"
    exit 1
    ;;
esac
exit 0
```

Пример скрипта:

```
#!/bin/sh
#
```

```
#  
  
. /etc/profile  
  
case "$1" in  
  start)  
  
    export XDG_RUNTIME_DIR=${XDG_RUNTIME_DIR:-/var/run}  
    export QT_QPA_PLATFORM=${QT_QPA_PLATFORM:-wayland}  
  
    # Wait for weston ready  
    while [ ! -e ${XDG_RUNTIME_DIR}/wayland-0 ]; do  
        sleep .1  
    done  
    /mnt/store/a7server/app&  
    ;;  
  stop)  
    killall app  
    ;;  
  *)  
    echo "Usage: $0 {start|stop}"  
    exit 1  
    ;;  
esac  
exit 0
```